



Smart Switch Relay Module

Product Code:
KASTA-S2400IBH

APP Installation

Visit www.kasta.com.au or your app store to download the free KASTA app.
iOS: requires iOS 9.0 or later.
Android: requires Android 4.4 or later.
Devices must support Bluetooth 4.0



Important Safety Information

- This product must be installed by a licensed electrician in accordance with all the requirements of AS/NZS 3000 (current edition) and other relevant Standards and Regulations.
- Electricity MUST be disconnected prior to installation. Failure to do so may result in serious injury and or loss of life.
- Indoor use only. Not suitable for damp or explosive environments.
- Complies to Australian Standards AS/NZS 60669.2.1, AS/NZS 60669.1, AS/NZS 4268, AS/NZS CISPR 15.

FEATURES

- Relay for switching a load on and off.
- Smart functions via phone/tablet with the app such as schedules, timers, scenes and groups.
- Simple 5 wire connection-A, N, Load, T1, T2.
- Install in conjunction with an appropriately rated momentary action mechanism to T1 and T2.
- Multi-way load switching possible using KASTA remote switches.
- Built-in thermal current overload protection.
- To prevent a reduction in Bluetooth® signal strength, install away from metal objects.

FUNCTION SETUP

*Must be connected to a momentary action mechanism across T1/T2 terminal to perform setup.

| | |
|--|-----------|
| ON/OFF SWITCH | 1 CLICK |
| Turns lights on or off. When turned ON, lights will adjust to previous brightness setting. | |
| DELAY TO OFF | 3 CLICKS* |
| Lights automatically turns off after set time. | |
| FACTORY RESET | 9 CLICKS |

Restores all settings back to factory.

*If successful, light will pulse the number of times that the switch was clicked, indicating function.

TECHNICAL SPECIFICATIONS

Supply: 220-240V AC 50Hz

Operating Temp: -20°C to 40°C

LED Load Wattage: 2W - 2400W

Thermal Derating: 25°C - 40°C (2400W-1200W)

Max Switch Load and Multi Gang: 2400W | 1, 1800W | 2, 1320W | 3 (Multi Gang Derating on single switch plate)

CONNECTION DIAGRAM

