

PURO^{G4}

**Product Code: PURO25W-EM-MS
PURO25W400R-EM**

- 1) Ensure mains power has been isolated/turned off.
- 2) Remove diffuser from base by rotating it in an anti-clock wise direction.
- 3) Position base plate with cables feeding through the central protection grommet.
- 4) Fix to ceiling or appropriate surface with screws provided or other appropriate method.
- 5) Install/connect cables into terminal block.
- 6) Select required colour temperature using the three position switches 3000K, 4000K, 5700K.
- 7) Replace diffuser ensuring the three locating pins on the baseplate align with the diffuser and tighten in a clock wise direction.
- 8) Restore power and test light for illuminates.

EMC: AS CISPR 15:2017

Installation

<p>1 TURN OFF POWER at the source.</p>	<p>2 Mark ceiling (Screw and cable locations), then drill 3 holes.</p>	<p>3 Install 3 drywall anchors.</p>	<p>4 Run power cord through the central hole of base and screw base to ceiling. Do not touch LED Chips while performing this step.</p>
<p>5 Connect power to terminals as shown above, then put on the PC protecting cover</p>	<p>6 Adjust hold-time, detection area, and daylight sensor by turning the knobs.</p>	<p>7 Switch to the appropriate colour temperature.</p>	<p>8 Reattach cover.</p>
	<p>5 With emergency kit</p> <ul style="list-style-type: none"> - Intelligent automatic recharging function. - 90 mins emergency operation. - LED charge status display. <p>6 With sensor</p> <ul style="list-style-type: none"> - Hold-time adjustable from 5 seconds to 30 minutes. - Day light sensor with adjustable threshold: Disable, 5lux. - Wide detection area, max. 10m. 		
<p>9 Restore power.</p>			

* The Installation must be carried out by an electrician