



### Powerpoint Double, Horizontal

Product Code:  
**H2PPHB**

#### APP Installation

Visit [www.kasta.com.au](http://www.kasta.com.au) or your app store to download the free KASTA app.  
iOS: requires iOS 9.0 or later.  
Android: requires Android 4.4 or later.  
Devices must support Bluetooth 4.0



#### Important Safety Information

- This product must be installed by a licensed electrician in accordance with all the requirements of AS/NZS 3000 (current edition) and other relevant Standards and Regulations.
- Electricity **MUST** be disconnected prior to installation. Failure to do so may result in serious injury and or loss of life.
- Indoor use only. Not suitable for damp or explosive environments.
- Complies to Australian Standards: AS/NZS 3112; AS/NZS 60669.2.1; AS/NZS 4268 and AS/NZS CISPR 15.
- No user serviceable parts inside.
- It is strongly recommended to have a surge protection device installed at the main switchboard. Products that are damaged by power surges are not covered by warranty.

#### FEATURES

- Control and monitor appliances with a standard 2 or 3-pin plug.
- 2x 10A individually switched power outlets.
- Simple 3 wire connection – A, N, E.
- Pair with KASTA remote switch devices for control (up to 8x maximum).
- Smart functions per outlet programmed via phone/tablet with the KASTA app. This includes schedules, timers, scenes and groups.
- Child Lock function per outlet (lock outlet in off state) activated from the button or the KASTA app.
- Energy monitoring function per outlet viewed from the KASTA app.
- Built in overvoltage, overcurrent and overtemperature protection.

#### FUNCTION SETUP

ON/OFF SWITCH	1 CLICK
Turns load on or off. Button LED indicator is blue when on.	
CHILD LOCK	4 SECOND LONG PRESS (WHEN OUTLET IS OFF)
Button LED indicator changes to green if successful after long press (four seconds). Long press (four seconds) again to deactivate.	
DELAY TO OFF	3 CLICKS
Load automatically turns off after set time selected via the app. LED indicator will flash 3 times if successful. 1 click to cancel, LED indicator will flash once.	
FACTORY RESET	9 CLICKS
Restores both outlets back to factory settings. *If successful, light and LED indicator light will pulse the number of times that the button was clicked, indicating function.	

#### TECHNICAL SPECIFICATIONS

- Supply:** 220-250V a.c. 50Hz
- Operating Temp:** -20°C to 40°C
- Maximum Load:** 2 x 10A (2400W)

#### CONNECTION DIAGRAM

