



Smart Switch Relay Mechanism

Product Code:
KASTA-S350BH-W

APP Installation

Visit www.kasta.com.au or your app store to download the free KASTA app.
iOS: requires iOS 9.0 or later.
Android: requires Android 4.4 or later.
Devices must support Bluetooth 4.0



Important Safety Information

- This product must be installed by a licensed electrician in accordance with all the requirements of AS/NZS 3000(current edition) and other relevant Standards and Regulations.
 - Electricity **MUST** be disconnected prior to installation. Failure to do so may result in serious injury and or loss of life.
 - Indoor use only. Not suitable for damp or explosive environments.
 - Complies to Australian Standards AS/NZS 60669.2.1, AS/NZS 60669.1, AS/NZS 4268, AS/NZS CISPR 15.
 - No user serviceable parts inside.
 - A load correction device - X2 Capacitor type 275Vac, 0.10µF, 40/110/56/B - has been included with your KASTA Switch Relay.
- If flickering of the luminaire load is experienced, connect the load correction device across the line output of the KASTA Switch Relay to improve performance.

FEATURES

- Relay for switching a load on and off.
- Smart functions via phone/tablet with the app such as schedules, timers, scenes and groups.
- Push Button Control.
- Fits most Australian Standard wall mech apertures.
- Simple 2 wire connection-Active in and load out.
- Integral blue backlight that can be enabled/disabled after installation.
- Multi-way load switching possible using KASTA remote switches.
- Built-in thermal current overload protection.

FUNCTION SETUP

ON/OFF SWITCH	1 CLICK
DELAY TO OFF	3 CLICKS*
BACKLIGHT ON/OFF	7 CLICKS
FACTORY RESET	9 CLICKS

Restores all settings back to factory.
*If successful, light will pulse the number of times that the switch was clicked, indicating function.

TECHNICAL SPECIFICATIONS

- Supply:** 220-240V AC 50Hz
- Operating Temp:** -20°C to 40°C
- LED Load Wattage:** 15W - 350W (Will require "Load Bypass" if less than 15W)
Small motors such as ceiling exhaust fans Max. 100 W (0.5 A @ 0.8 pf)
- Thermal Derating:** 25°C - 40°C (350W-175W)
- Max Switch Load and Multi Gang:** 350W | 1, 260W | 2, 190W | 3 (Multi Gang Derating on single switch plate)

CONNECTION DIAGRAM

