


Installation Instructions



Battery Powered 5-Button Controller

Product Code:
KASTA-5BCBH-W

APP Installation

Visit www.kasta.com.au or your app store to download the free KASTA app.
iOS: requires iOS 9.0 or later.
Android: requires Android 4.4 or later.
Devices must support Bluetooth 4.0



Important Safety Information

- For indoor use only. Not suitable for damp or explosive environments.
- WARNING: This product contains 2x CR2032 coin batteries. A coin battery can cause serious internal chemical burns if swallowed.
- WARNING: Dispose of used batteries immediately. Keep new and used batteries away from children. If you think batteries might have been swallowed or placed inside any part of the body, seek immediate medical attention.
- CAUTION: To prevent damage to the appliance do not use alkaline cleaning agents or solvents when cleaning, use a soft cloth and a mild detergent.
- Complies with Australian Standards AS/NZS 4268 and AS/NZS CISPR 15.

FEATURES

- 5 Capacitive Touch Buttons.
- Portable handheld device for easy control.
- Pairs to existing hard wired KASTA devices including: Switch Relays, Dimmers, Curtain controllers and many other devices.
- Configure smart functions via the KASTA app such as timers, scenes and groups.
- Built in magnetic base provides additional mounting options.

FUNCTION SETUP

ON/OFF	1 PRESS
Turns paired device on or off. When paired with a dimmable light, light will adjust to previous brightness level.	
DIM UP/DOWN	ONE LONG PRESS
When paired with a light, long press button to dim up or down. Release button to stop.	
FULL BRIGHTNESS	2 PRESSES
When paired with a light, sets light to full brightness.	
DELAY TO OFF	3 PRESSES*
Paired device turns off automatically after a time (configured in the app). Single click to cancel.	
VARIABLE	4 PRESSES*
Refer to the paired device for functionality.	
VARIABLE	5 PRESSES*
Refer to the paired device for functionality.	
PAIRING MODE	6 PRESSES
Pair a button with another KASTA device when prompted by the KASTA app.	
FACTORY RESET	9 PRESSES
9 clicks of any button, restores all settings back to factory. *If successful, the blue LED indicator will flash rapidly then change to a slow flash before entering sleep mode.	

APP ENABLED FUNCTION

RETRIGGER TIMER	1 PRESS
Enable delay to on/off. Function must be programmed through app first.	

TECHNICAL SPECIFICATIONS

Range: Up to 30m open air
Operating Temp: 0°C to 40°C
Battery: CR2032 Lithium (x2)
Battery Life: 1 year
IP Rating: IP44 (light-emitting area) IP40 (main body)
Dimensions: 125x51x44mm

CONNECTION DIAGRAM

